

## Panic / Help Button

Part Number: ZW01871KFC



## Features:

- People wellbeing and security monitoring
- Simple panic and help call button to raise an alarm
- Very long battery life with battery level feedback
- Perfect for care homes, banks, and betting shops
- Personal protection, lanyard based or discrete
- The HALO Smart panic key fob is a simple panic personal key fob
- The key fob is designed for applications in home automation and light commercial environment
- The technology uses a low-power RF radio system
- Application can include panic alarms for retail location, care homes, offices, lone working environments

Supply Voltage	3.7V (Lithium Polymer Battery)
RF Distance	Min. 30M indoor, 100M outdoor line of sight (subject to change due to environmental conditions such as walls, noise, materials etc.)
RF Frequency	868.4MH, 869.85MHz (EU)
Chip	Z Wave 500 series module
Battery	1 - 1.5 Years (based on 10x activation per day) USB Charged Device
Dimension	75(L) x 34(W) x 10(H) mm
Weight	28g
IP Classification	Indoor use
Operation Temperature	-10 ~ 45°C
Operation Humidity	95%RH max.